



Fore-edge

	Model	W60AP
Donanım	Flash	SPI NOR 16M
	DDR	128MB
	2.4G Frekans Bandı	2.4GHz – 2.484GHz
	2.4G WiFi Protokol	802.11b/g/n/ax
	5G Frekans Bandı	5.150GHz – 5.850GHz
	5G WiFi Protokol	802.11a/n/ac/ax
	2.4G Anten	2x 3dBi
	5G Anten	2x 3dBi
	Maksimum Rate	2.4G: MAX 600Mbps, 5G: MAX 1200Mbps
	WAN Port	1x 10/100/1000M WAN port, 48V PoE destekler
	LAN Port	4x 10/100/1000M LAN port
	PoE	802.3af
	Buton	Sıfırlama Butonu (Fabrika değeri için 6-10 sn basılı tutun)
	İşik	System
	Maksimum Güç	<14W
	Ebatlar	87 x 86 x 48 mm
	Ağırlık	0.28 Kg
	Çalışma İsisi	0°C ~ 40°C
Yazılım	Depolama İsisi	-40° ~ 70°C
	Çalışma Nem Oranı	%10 ~ %90 RH
	Depolama Nem Oranı	%5 ~ %95 RH
	Mod	Gateway mod: Cihaz, bir WAN bağlantı noktası aracılığıyla geniş alan ağına bağlanır ve ardından interneete bağlanmak için statik IP, DHCP veya PPPOE kullanır. AP modu: Cihaz, diğer istemcilere veya cihazlara giden kablosuz ağ sinyalini kapsar ve geniş alan ağına erişmeden önce Ethernet kablolarını kullanarak diğer yönlendiricilere bağlanır.

	<p>SSID broadcast</p> <p>Number of SSIDs: 4 (2.4GHz)+4 (5GHz), supporting Chinese SSIDs</p> <p>Hide SSID function</p> <p>Wireless authentication methods: OPEN, WPA/WPA2-PSK</p> <p>Channel and channel bandwidth can be set</p> <p>Wireless MAC address filtering: supports whitelist (100)</p> <p>VLAN ID: The VLAN-ID range must be between 3 and 4094, where 0 indicates not enabled</p> <p>Spectrum navigation (5G priority)</p> <p>WiFi timed shutdown function</p> <p>User isolation: wireless network isolation, AP internal isolation</p> <p>Transmission power setting</p> <p>Limited number of wireless clients, supporting a maximum of 100 users</p> <p>Provides WIFI analysis functionality for the current environment</p>
Yazılım	<p>Network Fonksiyonları</p> <p>Ipv4 address: supports static addresses, obtains addresses from management servers, and obtains addresses from network administrators</p> <p>DHCP server: It can be either a built-in DHCP server or an external DHCP server</p> <p>Cloud Platform Server</p> <p>Firewall function</p> <p>PPPOE function: supports PPPOE dialing function</p>
Cihaz Yönetimi	<p>Backup configuration information</p> <p>Restore Configuration Information</p> <p>Restore factory settings</p> <p>Reboot includes scheduled and immediate restarts</p> <p>Password modification</p> <p>Firmware upgrade, optional whether to restore factory settings after the upgrade is completed</p> <p>Time management includes system display time and time synchronization</p> <p>system log</p> <p>Fat and thin AP switching function</p>